

Preparations:

1. Download the firmware file for your ROXX device from the support page:
<https://roxlight.com/support/>
2. Copy the file to a USB stick in the root directory and not in a folder. The stick must not have more than 8 GB storage capacity and should be formatted „fat32“.
3. Make sure that both CRMX and BLE (Bluetooth Low Energy) are deactivated.

Update process:

1. Insert USB stick:
-> Insert the prepared USB stick with the firmware file into the USB port of the spotlight.
2. Select firmware file:
-> Press **Enter** on the control panel.
-> A list of the files on the USB stick is displayed.
-> Use the navigation buttons to select the relevant update file.
3. Confirm update:
-> Select the update file and press **Enter** to confirm the update.
4. Update process:
-> The spotlight now starts the update, which can be followed via the display. The update process is visually indicated by the individual colors lighting up and the fan turning up.
-> Wait until the update is complete. This may take a few minutes.
5. Restarting the lighting system:

-> Once the update is complete, the spotlight is restarted automatically.
-> The new firmware version is shown on the display.
-> You can check the current firmware version at any time via the menu under **Info > Firmware**.

Completion:

- > Remove the USB stick after the successful update.
- > If required, reactivate CRMX and BLE via the menu.

Your NEO is now successfully updated and ready for use.